

## VF5666-0M

### Sounder Control Module



#### Standard Features

- Allows sounders to be operated continuously or be pulsed, 1 second on, 1 second off
- May be synchronized when in pulsed operation
- Can also be used for public address speakers
- Visible LED

#### Overview

The Sounder Control Module monitors and controls a circuit of alarm notification appliances or speakers. It is mounted on a plastic face plate for use with a 4" square or 2 gang electrical box. The module requires a separate 24VDC supply to power notification appliances.

In addition to individual Sounder Control Module operation, multiple modules can be controlled simultaneously as a group.

A red LED flashes in synchronization with the current pulse for reply from the device.



#### Technical Specifications

**Dimensions:** 4 1/2" x 4 1/2" x 1"

**Temperature Range:** 32°F to 120°F

**Humidity:** 10 to 93% RH Non-Condensing

**Wiring Size:** 24AWG - 14AWG

**Signal Line Circuit(SLC):** Supervised power limited

**Working Voltage:** 17-28VDC

**Modulation Voltage:** 5-9V (Peak to Peak)

**Supervisory Current:** 1.3mA

**Surge Current:** 7.5mA

**Maximum Current:** 4mA